

baracoda



BlueLink Printer

The ultimate cable-free printing solution!

BlueLink Printer Combo Adapter creates cable-free printing connections between your desktop PCs and printers. It is compatible with all Bluetooth v1.1 certified devices.



Easy operation and setting up

Support both USB and 1284 printer port interfaces

Connect your computing devices and printers up to 100 meters away without cables

Support for Microsoft Windows 98SE, Me, 2000 and XP

Both SPP and HCRP print service profiles supported

© Baracoda™ - January 2005 - Specifications are subject to change without notice. Non contractual pictures.

The Bluetooth name and the Bluetooth Registered trademark are owned by Bluetooth SIG, Inc, and are used by Baracoda under licensed. The Baracoda name and the Baracoda trademark are owned by Baracoda.

Because connection isn't just about wires



Technical Specifications



Class 1 (100 meters range)

Certification	FCC, CE, BQB
Standard	Bluetooth v1.1
Frequency Band	2.4~2.4835GHz unlicensed ISM band
Modulation Method	GFSK, 1Mbps, 0.5BT Gaussian
Spread Spectrum	FHSS (Frequency Hopping Spread Spectrum)
Services supported	SPP and HCRP print services
Transfer rates (Max)	1 Mbps
RF Output Power	Class 1
Working distance	Greater than 100m in free space
Sensitivity	<-88dBm at < 0.1% BER
Power consumption	
Tx Typical:	115mA
Rx Typical:	75mA
Standby Mode:	15mA
Input power	7.5V DC
I/O Interface	USB, IEEE-1284
LED indicator Power / Bluetooth active / Printing active	
Environment	
Operation temperature:	0 oC ~ + 60 oC
Storage temperature:	-10 oC ~ +70 oC
Humidity:	5 ~ 90% non-condensing

BARACODA SA (Europe Office)
 30 avenue de l'Amiral Lemonnier - 78160 Marly le Roi - FRANCE
 Ph: +33 1 30 08 89 00 - Fx: +33 1 30 08 89 98
 Email: contact@baracoda.com

Baracoda, Inc. (US Office)
 45 Main street - Suite 616 - Brooklyn, NY 11201 - USA
 Ph: 718 488 9600 - Fx: 718 488 9601
 Email: contact@baracoda.us